



RGBWW HAND REMOTE

CONTROLLER SERIES

PROJECT:

PREPARED BY:

DATE:

TYPE:



FEATURE

- Programmable RGB+CCT RF remote controller with 434MHz/869.5MHz/916.5MHz frequency available
- Sleek streamline design with high end PC material, comfortable to touch
- User-friendly interface, easy and simple operation
- Enables 5 channel control of RGB and dual color (warm white and cold white) as well as programmable function
- Ultra-sensitive tempered glass touch color wheel, accurate and fast RGB color tone adjustment
- R, G, B and CCT channels can be controlled separately
- Programmable function by choosing colors (maximum 5 colors) and touch the "P" key
- Pattern changing speed adjustable
- 4 running modes including jump, flash, fade and strobe are available for the programmed colors
- Control 4 zones separately or synchronously, each zone can be set endless receivers, each receiver maximally be controlled by 8 different remotes
- Set 4 scenes
- Synchronization function of pattern changing ensures consistent change forever
- Enable to dim brightness of each R, G, B, W channel, in order to mix millions colors
- Receivers can work with WiFi-RF converter after installing software on IOS and Android system

PERFORMANCE

• Output	RF signal	• Waterproof	IP20
• Power Supply	4.5V(3xAAA battery)	• Relative humidity	8% to 80%
• Power Frequency	869.5/916.5/434MHz	• Dimensions	6.02" x 2.05" x 0.75"
• Operating Temperature	0-40°C		(153mm x 52mm x 19mm)

ORDERING GUIDE

Model	Channel	Zone Amount	Application	Finish
LB56112	5 Channel (RGBWW)	4 Zone	Hand-Held	Black

**Not compatible with magnetic drivers.*



RGBWW HAND REMOTE

CONTROLLER SERIES

PROJECT:
PREPARED BY:
DATE:
TYPE:

DIMENSION

